# Radium

# **Technical information**

# **DRIVER 50W/1200mA IP20**

Constant current LED drivers for LED modules with an operating current of 1200mA and an output voltage between 33V and 42V. Suitable for protection class I and protection class II luminaires. Flicker free with high efficiency and long service life of 70,000h  $@T_c 68^{\circ}C$ . For AC operation at 230V 50-60Hz or DC operation at 200-280V DC.

Recommended for the following Radium LED T8 Neo Tube:

- 43719852 LED T8 NEO 58 840/G13 LED T8 NEO 58 865/G13
  - 43719853



#### Drawing



### **Technical Data**

General	Data	

Code	DRIVER 50W/1200mA IP20
Article No.	OTNA4035
EAN10	4003556010871
EAN40	4003556410879
Weight [g]	180 g
Length [mm]	245 mm
Width [mm]	30 mm
Height [mm]	21 mm
Service Life @T <sub>c</sub> 73°C	50,000 h
Service Life @T <sub>c</sub> 68°C	70,000 h
Service Life @T <sub>c</sub> 63°C	100,000 h
Guarantee	5 years

#### **Operating Conditions**

Permissible ambient temperature T <sub>a</sub> [°C]	-30°C+50°C
Permissible storage temperature [°C]	-30°C+80°C
Permissable T <sub>c</sub> temperature [°C]	-30°C+73°C
Max. permissable T <sub>c</sub> temperature [°C]	+73°C
Permissible air moisture	10-90%RH
Degree of protection (IP)	IP20
Protection class	1

Radium Lampenwerk GmbH P.O. Box 1440 - 51678 Wipperfürth

+49-2267 - 81 - 1 FAX +49-2267 - 81 - 231

Information no. 9906-01-2112

Validity: The technical information sheets (TI sheets) are updated at irregular intervals! The user is responsible for the validity and up-to-dateness of this TI sheet. With the publication of this TI sheet, all previous editions for this lamp type lose their validity

# Radium

#### Electrical Parameter Output

Rated power [W]	39,6 – 50,4 W
Permissible voltage [V DC]	33 – 42 V
Output current [mA]	1200 mA
Output current tolerance [mA]	± 5 %
Output P_ST_LM	≤1
Output SVM	≤ 0,4
Offset time @ AC 230V	<0,5 s
Kind of protection embodied	Short-circuit proof, open-circuit-proof

#### **Electrical Parameter Input**

Mains voltage range [V AC]	220 – 240 V
Alternating voltage range [V AC]	200 – 264 V
Direct voltage range [V DC]	200 – 280 V
Mains frequency [Hz]	50 – 60 Hz
Nominal current [A]	0.4 A
Mains power factor [λ]	≥0.94 @ 230 V <sub>ac</sub>
THD	≤20 %
Efficiency	≥90 %
Inrush current	≤58A & 163µs @ 230 V <sub>ac</sub>
Power consumption in Stand-by	≤0.5 W
Surge voltage strength L-N	1 kV
Surge voltage strength L/N-PG	2 kV

#### Safety and electromagnetic compatibility

Certificates	ENEC, CE
Safety standards	EN61347-1:2015, EN61347-2-13:2014/A1:2017, EN62384:2016/A1:2009, EN61347-2-13:2014/A1:2017, EN61347-1:2015, EN62493:2015 IEC 61347-1:2015, IEC61347-2-3:2014, IEC61347-2-13:2014/AMD1:2016
EMI	CE-EMC/RCM: EN55015, EN61000-3-2, EN61000-3-3
EMS	CE-EMC/RCM: EN61000-4-2,3,4,5 (L-N:1KV L/N-PG:2KV),6,11
RoHS	RoHS 2.0 (EU) 2015/863

#### **Electrotechical Parameter**



Radium Lampenwerk GmbH P.O. Box 1440 - 51678 Wipperfürth ☎ +49-2267 - 81 - 1
FAX +49-2267 - 81 - 231

Information no. 9906-01-2112

Validity: The technical information sheets (TI sheets) are updated at irregular intervals! The user is responsible for the validity and up-to-dateness of this TI sheet. With the publication of this TI sheet, all previous editions for this lamp type lose their validity

# Radium

# **Technical information**

#### Service life



### Wiring diagram



#### Fuse rating



Characteristic	Current	Max. no. of devices	
В	10A	9	
	16A	15	
с	10A	15	
	16A	25	
Ipeak / Twidth	≤58A / 163uS		

### Notes

- It is recommended to install overvoltage and undervoltage protection devices and surge protection devices in the power supply circuits of the light fixtures to ensure safety before connecting to electricity.
- As an accessory, the LED driver is not the only factor determining the EMC performance of the LED light fixture. The structure and the wiring of the light fixture are also relevant.
- Unless otherwise stated, the parameters of the power factor, harmonics and efficiency were test results under the conditions ambient temperature of 25°C, humidity of 50%, input voltage of 230Vac(50Hz) and full load.
- Use this product according to the specifications. Otherwise there may be malfunction.
- Use of light fixtures that have not been certified or are not compatible with the LED drivers may cause fire or other hazards.
- Man-made damage, any use beyond the specification and non-original-factory modification are not covered by warranty.

Radium Lampenwerk GmbH P.O. Box 1440 - 51678 Wipperfürth ☎ +49-2267 - 81 - 1
FAX +49-2267 - 81 - 231

Information no. 9906-01-2112

Validity: The technical information sheets (TI sheets) are updated at irregular intervals! The user is responsible for the validity and up-to-dateness of this TI sheet. With the publication of this TI sheet, all previous editions for this lamp type lose their validity